

INTRODUCTION

This converter box converts digital HDMI or DVI signals into analog VGA and stereo audio. It is a perfect solution for connecting video cards (desktop or Laptop) or consumer electronics devices such as game consoles or home theater receivers that offer an HDMI Out port to a VGA display

FEATURES

- * Easy to Use: Installs in seconds, no settings and it is a resolution pass-through converter
- * It is purely for conversion between video formats but not convert the input/output video resolutions;
- * Audio output format: 2 channel LPCM:
- * Compliant with HDMI 1.3
- * Supports 165MHz/1.65Gbps per channel (6.75Gbps all channels) bandwidth for HDMI Input
- * HDMI resolutions:
480P@60Hz, 720P@50/60Hz, 1080P@50/60Hz. 800*600@60 Hz, 1024*768@60 Hz, 1920*1080@60Hz
- * VGA resolutions:
640*480@60Hz, 1280*720@50/60Hz, 1920*1080@50/60Hz. 800*600@60 Hz. 1024*768@60 Hz

SPECIFICATIONS

Signal Input	HDMI
Input Video Signal	0.5-1.0 volts p-p
Output Video	VGA signal
DTV/HDTV	480P/576P/720P/1080P
Video Amplifier Bandwidth	1.65Gbps/165MHz
Vertical Frequency Range	60Hz
Progressive Resolutions(60Hz)	480p, 576p, 720p, 1080p
Limited Warranty	1 Year Parts and labor
Operating Temperature	0°C to 70°C
Operating Humidity	10% to 85% RH (no condensation)
Storage Temperature	-10°C to +80°C
Storage Humidity	5% to 90% RH (no condensation)
Power Supply	5V DC
Power consumption(MAX)	5W
Converter Unit Cert	FCC, CE
Power Supply Cert	CE, FCC
AC Power Adapter	US standard, UK standard and so on
User Manual	English Version

Note: Specifications are subject to change without notice.

PACKAGE CONTENTS

- 1) Main unit
- 2) 5V Power supply
- 3) User Manual

Distributed by:
CHARMEX INTERNACIONAL, S.A.
Maresme, 103
08019 - Barcelona
charmex@charmex.net
+34933036620